CR2032 BATT

PROJECT:

LOCATION:

TRULUX Tunable Dial Control

TYPE:

CAT:

Description

Trulux tunable dial control for tunable CCT light control; single zone operation.

Features

- Push dial for On/Off or current color temperature control

 rotate for full range dimming (1-100%)
- Double push dial for color temperature selection (2700K-6000K with Trulux HTL-TW tape light)
- Available in wall mount or table top styles
- Smooth glass faceplate with brushed satin dial
- Radio frequency (RF) signal range up to 65 feet
- Battery operated (CR2032 battery included)
- Control multiple receivers in a single zone
- Requires Trulux RF receiver for operation (sold separately)

Mounting

Wall Mount: Flush mount to wall or flat surface (1-3/4" x 2-5/8" cut-out) Table Top: Includes table top stand

Applications


Dimming, CCT, and zone control for tunable CCT

Warranty

3 years

Technical Information

Voltage	3V DC Operation voltage (battery operated 10mA power consumption)				
Battery Type	CR2032 (Included)				
Frequency	916.5MHz RF wireless				
Operating Temperature	0° - 40°C				
Relative Humidity	8% - 80%				
Rating	FCC Compliant, RoHS Compliant, dry location				



Required Receivers

Part Number	Description	Application	Input	Current	Output	Listing	Dimensions
REC-5A-4Z	Trulux RF Constant Voltage Receiver	Dry location	12-36V DC	4x5A	4x(60-180)W	RoHS	7-1/16" x 1-13/16" x 6-23/32" (178.9mm x 45.5mm x 18.6mm)



Page 1 of 1



